

Installation Instructions



TimeMaster GMXFM1D Series Electronic Time Controls

APPLICATION

The GMXFM1D Series are universal electronic time switches within UL TYPE 1 indoor enclosures intended for the control of lighting, heating, air conditioning, pumps, motors, or general electrical circuits in residential, commercial, industrial and agricultural facilities. Basic models are:

Series	Description
GMXFM1D20	1 channel SPDT 20 program electronic

SPECIFICATIONS

Switch Rating: SPDT Switch

GMXFM1D Series Switch Ratings:

N.O. Contact:

- 1/2 hp, 120 VAC
- 1 hp, 240 VAC
- 8 A, 24 VDC resistive
- 15 A, 277 VAC resistive
- 12 A Ballast, 120 VAC
- 8 A Ballast, 240 VAC
- 720 VA 240 VAC Pilot Duty
- 360 VA 120 VAC Pilot Duty
- 1000 W Tungsten, 240 VAC
- 600 W Tungsten, 120 VAC

N.C. Contact:

- 15 A, 277 VAC resistive
- 8 A, 24 VDC Pilot Duty
- 360 VA, 120 VAC Pilot Duty

3 year Reserve (Non-Replaceable Battery)

ENVIRONMENTAL RATINGS

Ambient Temperature: 5°F to 131°F (-15°C to 55°C)

WIRING CONNECTIONS

Screw clamp terminals for up to AWG #10 wires

Agency Approvals: UL Listed

INSTALLATION

Note: For outdoor locations, Raintight or wet location conduit hubs that comply with requirements of UL 514B (standard for fittings for conduit and outlet boxes) are to be used.



GMXFM1D20


1. Remove 2 screws retaining the interior cover panel and remove panel by prying out with a thin blade at the top.
2. Select knockouts to be used. Remove the inner (1/2") knockout by inserting a screwdriver in the slot and carefully punch knockout loose. Remove slug. If the 3/4" knockout is required, remove the outer ring with pliers after removing the 1/2" knockout. Smooth edges with knife if necessary.
3. Place enclosure in desired mounting location and mark the three mounting holes.
4. Drill holes for #10 screws, start screws in holes.
5. Place enclosure over screws and tighten screws.
6. Connect conduit hubs to conduit before connecting the hubs to the enclosure. After inserting hubs into enclosure, carefully tighten hub lock nut. Do not over-torque.
7. Wire in accordance with National and Local Codes.
8. Replace interior cover panel and 2 screws.

Grounding: This enclosure is of plastic construction and does not require a ground connection and does not require bonding in pool applications.


This enclosure does not provide grounding between conduits. When using non-metallic conduit or cable, connect the ground wires of all cables together with a wire nut. When metallic conduit is used, use grounding type bushings and a jumper wire between each conduit.

Typical Wiring Diagrams

12/24 VDC, 24 VAC Timer, 120 VAC Load



120-277 VAC Timer 120-277 VAC Load



GMXFM1D Series Program Schedules

Prog	ON/OFF	h	m	Day(s)
Ex	On	7 am	30	Mon., Tue., Wed., Thurs., Fri.
1				
2				
3				
4				
5				
6				
7				
8				
9				
10				
11				
12				
13				
14				
15				
16				
17				
18				
19				
20				
21				
22				
23				
24				
25				
26				
27				
28				
29				
30				
31				
32				
33				
34				
35				
36				
37				
38				
39				
40				
41				
42				
43				
44				
45				
46				
47				
48				
49				
50				