

## Transformer - 300 W Pool & Spa Safety Transformer, Beige Steel Enclosure, Input 120V, Output 12,13,14V

Item PX300



### PRODUCT DESCRIPTION

These safety transformers are specifically designed to supply 12-14 VAC and are suitable for direct connection to underwater pool/spa lights. A grounded shield between the primary and secondary winding assures safe operation. Built-in circuit protection will disconnect power to the transformer in case of an overload.

### FEATURES

- ▶ Mounting brackets on the top and bottom
- ▶ Built-in circuit protection disconnects power temporarily in case of overload
- ▶ Complies with NEC Code 680.23 requirements for underwater luminaires

### APPLICATIONS

- ▶ Landscape Lighting
- ▶ Underwater Lighting

### TECHNICAL DATA

#### General

|                                |  |
|--------------------------------|--|
| Model Number                   | PX300  |
| Description                    | 300 W Pool & Spa Safety Transformer, Beige Steel Enclosure, Input 120V, Output 12,13,14V |
| UPC Code                       | 078275024106   |
| Brand                          | Intermatic   |
| Country of Origin (Intermatic) | MEXICO   |
| Warranty Period                | 1-Year limited   |

#### Mechanical Specifications

|                |                |
|----------------|----------------|
| Enclosure Type | 3R Beige metal |
|----------------|----------------|

#### Dimensions

|                                   |                             |
|-----------------------------------|-----------------------------|
| Product Dimensions (H x W x D) in | 7.25 x 5.25 x 4.5 in        |
| Knockout Dimensions Bottom        | (4) combination 1/2" - 3/4" |
| Knockout Dimensions Back          | (2) combination 1/2" - 3/4" |
| Knockout Dimensions Left          | (2) combination 1/2" - 3/4" |
| Knockout Dimensions Right         | (2) combination 1/2" - 3/4" |

#### Electrical Specifications

|                               |                        |
|-------------------------------|------------------------|
| Output Voltages               | 12 VAC; 13 VAC; 14 VAC |
| Maximum Power Consumption (W) | 300 W                  |
| Transformer (W)               | 300                    |
| Transformer Input Voltage     | 3 A, 120 VAC, 60 Hz    |
| Transformer Output Voltage    | 12, 13, 14 VAC         |

#### Packaging

|                                       |                       |
|---------------------------------------|-----------------------|
| Product Weight (kg)                   | 4.99                  |
| Unit Carton Dimensions (H x W x L) in | 7.88 x 4.56 x 5.69 in |
| Product Weight (lbs)                  | 11                    |

### Standards and Certifications

|  |                 |
|--|-----------------|
| CSA Certification                        | cCSAus          |
| Other Certifications and Compatibilities | NEC Code 680.23 |
| California Proposition 65                | DEHP            |

---

## ACCESSORIES



ET-NF  
RC Snubber Noise Filter 24-277VAC/DC for Electronic Controls