



Project:	Туре:
Prepared By:	Date:

Driver Info		LED Info	
Туре	Constant Current	Watts	23W
120V	0.19A	Color Temp	4000K (Neutral)
208V	0.11A	Color Accuracy	72 CRI
240V	0.10A	L70 Lifespan	100,000 Hours
277V	0.09A	Lumens	3,472 lm
Input Watts	21.2W	Efficacy	163.8 lm/W

# **Technical Specifications**

# Lightcloud

## **Lightcloud Controller Installed:**

Integrated/embedded networked lighting control, luminaire-level lighting control. Fixture, Zone, and plug-load control from one powerful device. LLLC - capable of switching, 0-10Vdimming, power/energy monitoring. Can also be used to extend the range of the Lightcloud mesh network communication protocols. Offers the capability to set the maximum light output to a less-than-maximum state of an individual luminaire at the time of installation or commissioning. The High-End trim functionality is field reconfigurable via the Lightcloud mesh network communication protocols. The Lightcloud controller can be attached to the fixture, junction box, or electrical panel.

DLC system - NHCZ2BIA17L Learn more about Lightcloud.

#### Compliance

#### **UL Listed:**

Suitable for wet locations

# IESNA LM-79 &lm-80 Testing:

RAB LED luminaires and LED components have been tested by an independent laboratory in accordance with IESNAIm-79 and Im-80

#### **DLC Listed:**

This product is listed by Design Lights Consortium (DLC) as an ultra-efficient premium product that qualifies for the highest tier of rebates from DLC Member Utilities. Designed to meet DLC 5.1 requirements.

DLC Product Code: P7ANI2ZU

# Performance

# Lifespan:

100,000-Hour LED lifespan based on IES LM-80 results and TM-21 calculations

# Wattage Equivalency:

Equivalent to 70W Metal Halide

# **LED Characteristics**

#### I FDs

Multip-chip, high-output, long-life LEDs

#### Construction

# **Cold Weather Starting:**

The minimum starting temperature is -40°C (-40°F)

#### **Maximum Ambient Temperature:**

40°C (104°F)

#### Housing:

Die-cast aluminum

# Reflector:

Aluminum alloy

#### Lens:

Glass

#### Gaskets:

High-temperature silicone gaskets

# Mounting:

Surface mount

## Finish:

Formulated for high durability and long-lasting color

## Green Technology:

Mercury and UV free. RoHS-compliant components.

# **Electrical**

# **Drivers:**

Constant Current, 120-277V, 50/60 Hz, 120V: 0.19A, 208V: 0.11A, 240V: 0.10A, 277V: 0.09A

# Dimming Driver:

Driver includes dimming control wiring for 0-10V dimming systems. Requires separate 0-10V DC dimming circuit. Dims down to 10%.

#### THD:

10% at 120V, 14.55% at 277V



# **Technical Specifications (continued)**

#### **Power Factor:**

99.1% at 120V, 91.2% at 277V

# **Surge Protection:**

2kV

# Other

#### Note:

All values are typical (tolerance +/- 10%)

#### Warranty:

RAB warrants that our LED products will be free from defects in materials and workmanship for a period of ten (10) years from the date of delivery to the end user, including coverage of light output, color stability, driver performance and fixture finish. RAB's warranty is subject to all terms and conditions found at rablighting.com/warranty.

#### **Buy American Act Compliance:**

RAB values USA manufacturing! Upon request, RAB may be able to manufacture this product to be compliant with the Buy American Act (BAA). Please contact customer service to request a quote for the product to be made BAA compliant.

# 14" 356 mm 7 1/2" 191 mm

## **Features**

Affordable wall pack with traditional look

Ultra-high efficacy

Covers footprint of mid-size HID wall packs

100,000-Hour LED lifespan

# WP2LED34L-740U/LC



Family	Lumen Pack Wattage	CRI/Color Temp	Finish	Voltage	Options
WP2LED	34L -	- 740		U	/LC
	<b>34L</b> = 3400lm, 23W <b>49L</b> = 4900lm, 34W	<b>750</b> = 70 CRI, 5000K <b>740</b> = 70 CRI, 4000K <b>730</b> = 70 CRI, 3000K	Blank = Bronze W = White	U = 120-277V, 0-10V Dimmimg H = 480V, 0-10V Dimming	Blank = No Options  /PCU = 120-277V Button Photocell  /PCS = 120V Swivel Photocell  /PCS2 = 208V-277V Swivel Photocell  /PCS4 = 480V Swivel Photocell  /MVS = Microwave Motion Sensor  /E2 = 120-277V Battery Backup  /LC = Lightcloud® Controller