



| Project:     | Туре: |
|--------------|-------|
| Prepared By: | Date: |

| Driver Info | )                 | LED Info       |                  |
|-------------|-------------------|----------------|------------------|
| Туре        | Constant          | Watts          | 113/85/58W       |
| 120V        | 0.96A/0.70A/0.48A | Color Temp     | 3000/4000/5000K  |
| 208V        | 0.55A/0.41A/0.28A | Color Accuracy | 83-85 CRI        |
| 240V        | 0.47A/0.36A/0.26A | L70 Lifespan   | 100,000 Hours    |
| 277V        | 0.44A/0.34A/0.25A | Lumens         | 7,533-14,968 lm  |
| Input Watts | 55.5-114.6W       | Efficacy       | 119.3-143.7 lm/W |
|             |                   |                |                  |

# **Technical Specifications**

# **Field Adjustability**

#### Field Adjustable:

Field Adjustable Light Output: 113W/85W/58W (factory default: 85W) Color temperature selectable by 3000K, 4000K and 5000K (factory default: 4000K)

# Compliance

#### **UL Listed:**

Suitable for wet locations

# DLC Listed:

This product is listed by Design Lights Consortium (DLC) as an ultra-efficient premium product that qualifies for the highest tier of rebates from DLC Member Utilities. Designed to meet DLC 5.1 requirements.

DLC Product Code: S-7SSG86

# Electrical

# Driver:

113W: Constant Current, Class 2, 120-277V, 50/60 Hz,120V: 0.96A, 208V: 0.55A, 240V: 0.47A, 277V:

85W: Constant Current, Class 2, 120-277V, 50/60 Hz,120V:0.70A, 208V: 0.41A, 240V: 0.36A, 277V: 0.34A 58W: Constant Current, Class 2, 120-277V, 50/60 Hz,120V:0.48A, 208V: 0.28A, 240V: 0.26A, 277V: 0.25A

#### **Dimming Driver:**

Driver includes dimming control wiring for 0-10V dimming systems. Requires separate 0-10V DC dimming circuit. Dims down to 10%.

#### THD:

8.22% at 120V, 10.32% at 277V

#### **Power Factor:**

99.2% at 120V, 88.6% at 277V

#### Photocell:

Integrated photocell included with on/off switch

# **Surge Protection:**

4kV

## Flicker:

<30%

#### Performance

#### Lifespan:

100,000-Hour LED lifespan based on IES LM-80 results and TM-21 calculations

#### Wattage Equivalency:

113W: Replaces up to 750W Metal Halide (MH) or 400W High Pressure Sodium (HPS) 85W: Replaces up to 400W Metal Halide (MH) or 310W High Pressure Sodium (HPS) 58W: Replaces up to 350W Metal Halide (MH) or 250W High Pressure Sodium (HPS)

#### **LED Characteristics**

#### I FDs:

Long-life, high-efficacy, surface-mount LEDs

#### **Color Consistency:**

7-step MacAdam Ellipse binning to achieve consistent fixture-to-fixture color

# **Color Uniformity:**

RAB's range of Correlated Color Temperature follows the guidelines of the American National Standard for Specifications for the Chromaticity of Solid State Lighting (SSL) Products, ANSI C78.377-2017.

#### Construction

#### **Full Cutoff:**

Allows for conformance to the IDA's fully shielding requirement, emitting no light above 90 degrees.

#### Housing:

Die-cast aluminum

#### Lens:

Acrylic lens

# Reflector:

Alanod

## **Cold Weather Starting:**

The minimum starting temperature is -40°C (-40°F)



# **Technical Specifications (continued)**

#### **Maximum Ambient Temperature:**

Suitable for use in up to 40°C (104°F)

## **Green Technology:**

Mercury and UV free. RoHS-compliant components.

#### Finish:

Formulated for high durability and long-lasting color

#### Installation

#### Mounting:

Integrated junction box for wall mounting.

# Lightcloud

#### **Lightcloud Blue Sensor Installed:**

Lightcloud Blue is a Bluetooth Mesh wireless lighting control system that allows you to control RAB's various compatible devices. With RAB's patented Rapid Provisioning technology, devices can be quickly and easily commissioned for residential and large commercial applications using the Lightcloud Blue mobile app. Each device in a system can communicate with any other device, eliminating the need for a Gateway or Hub and maximizing the control system's reach.

DLC system - N1XMLOEATBA (Interior); NHCZ2BIA17L (Exterior)

Learn more at www.lightcloud.com.

#### **Gateway Required:**

No

#### Communication Protocol:

Bluetooth Mesh

# Range:

Indoor: Up to 60 feet between standard building materials. Building materials such as brick, concrete, and steel construction may require additional Lightcloud Blue devices to extend around an obstruction; Up to 200 feet clear line of sight.

Outdoor: Up to 60 feet clear line of sight; Up to 18 feet around corners

## Spacing Criteria:

Lightcloud Blue devices should be placed within the specified range to communicate within the Bluetooth Mesh network.

# **Factory Reset:**

Method 1: Delete from App

Open the app and access the device settings for the paired device. Be sure that the device is online and select 'Delete from Site'. The device will flash on/off 5 times and return to full brightness.

#### Method 2: Manual

Power the device off and on 5x consecutively. Do not allow less than 4s to elapse from switching off to on. Do not allow more than 2s to elapse from switching on to off. The device will flash 3x, then reset to 100% brightness at default CCT.

#### Method 3: Rapid Reset Tool

The Rapid Reset process must be done by a professional electrician qualified by RAB. Reach out to your RAB sales manager to request a Rapid Reset Tool. The tool simply needs to be placed directly on the small Lightcloud Blue logo on the device for 2s or until the lamp/luminaire flashes 3x, then resets to 100% brightness at the default CCT.

#### **Sensor Settings**

#### **Sensor Connection Type:**

Pogo pin

#### Max Mounting Height:

50 ft

#### **Detection Range:**

50 ft diameter mounted at 50 ft

# Sensor Technology:

Microwave (MVS)

# **Sensor Mounting:**

Externally mounted to fixture using Right Angle Arm Support (RAAS[B]).

## **Default Setting:**

Uncommissioned State: Motion Sensitivity: High

Brightness when triggered: 100%

Hold time: 20 minutes Standby to dim: 20%

Standby time: 1 minute When vacant: Off

#### Commissioned State:

Once pair, the sensor will default to disabled. Once enabled the following settings apply:

Motion Sensitivity: High

Brightness when triggered: Last on status

Hold time: 20 minutes Standby to dim: 20% Standby time: 1 minute When vacant: Off

## **Sensing Type:**

Occupancy or Vacancy (option to disable or set as an independent sensor)

# **Occupied Actions:**

On or On at a Dim Level

#### Vacant Actions:

Off or On at a Dim Level

#### **Occupancy Timeout:**

1 minute to 240 minutes

#### **Daylight Sensing:**

The sensor will determine to trigger the light(s) on or not based on the daylight threshold level set in the Lightcloud Blue mobile app.

#### **Daylight Threshold:**

150 lux to 1500 lux

#### Other

# Warranty:

RAB warrants that our LED products will be free from defects in materials and workmanship for a period of five (5) years from the date of delivery to the end user, including coverage of light output, color stability, driver performance and fixture finish. RAB's warranty is subject to all terms and conditions found at rablighting.com/warranty.

#### **Buy American Act Compliance:**

RAB values USA manufacturing! Upon request, RAB may be able to manufacture this product to be compliant with the Buy American Act (BAA). Please contact customer service to request a quote for the product to be made BAA compliant.



# Adjustable Sensor Settings?:

Yes, using the Lightcloud Blue mobile app

# Dimensions 10 1/4" 9 3/4" 10 7/16" 10 7/16"

# **Features**

- 100,000-Hour LED lifespan
- 0-10V dimming standard
- 5-Year, no-compromise warranty

| Ordering Matrix |                             |                                    |  |                          |   |   |  |
|-----------------|-----------------------------|------------------------------------|--|--------------------------|---|---|--|
| Family          | Size/Wattage                | Mounting                           | Color Temp                                       | Finish                   | Driver                                    | Options   |  |
| WPLED           | L                           |                                    |  | W                        |   | /LCBS/MVS   |  |
|                 | <b>L =</b> Large 113/85/58W | Blank = Integrated<br>Junction Box | <b>Blank =</b> 3000/4000/5000K CCT<br>Adjustable | Blank = Bronze W = White | <b>Blank =</b> 120-277V,<br>0-10V Dimming | Blank = Integrated Photocell /LCBS/MVS = Lightcloud Blue w/MVS Sensor |  |