

NAPKED-5040HW / NAPKED-5060HW

12V Constant Voltage Dimmable Hardwire Electronic Driver

Source: 120V Input / 12V Output
35W or 60W

Type _____

Project _____

Catalog No. _____

Notes _____

PRODUCT DESCRIPTION

12V enclosed dimmable driver to be used with Nora Lighting's 12V systems.

FEATURES

- Constant Voltage electronic driver
- Triac or ELV dimming
- Conduit access wiring compartment
- Meet Class II output limits
- 12V DC rated output
- Includes 10' power line connector (NALTL-10)
- cULus listed enclosure & cULus recognized driver

ELECTRICAL

Input Voltage: 120V

Output Voltage: 12VDC

Wattage: 35W (NAPKED-5040HW) or 60W (NAPKED-5060HW)

Load: Operates loads up to 80% for best performance

Dimming: Triac or ELV

Protection: Short circuit, over voltage and over-temperature protection

COMPATIBLE NORA 12V SYSTEMS

LED Drivers are compatible with Nora Lighting's 12V systems

SERIES	DESCRIPTION
NUTP4	12V Standard Tape Light
NUTP6	12V RGB Color Changing Tape Light
NMP-LED	12V Josh Puck Light
NM1-170	12V 1" M1 Series

OPTIONAL ACCESSORIES

NALTL-10: 10' Power Line Connector (included)

NALTL-30: 30' Power Line Connector


NATL-302W: Power Line Splitter, white cable. Splits power line connector into two separate connections.

LABELS AND LISTINGS

- cULus Listed
- FCC compliant



PRODUCT IMAGES & DIMENSIONS



NAPKED-5040HW / NAPKED-5060HW
12V Constant Voltage
Dimmable Hardwire Electronic Driver



NALTL-10 / NALTL-30
Power Line Connector (10' included)



NATL-302W
Power Line Splitter

12V Constant Voltage Dimmable Hardwire Electronic Driver

Output Voltage / Wattage

NAPKED-5040HW = 12V Output / 35W

NAPKED-5060HW = 12V Output / 60W

Optional Accessories

Description

NALTL-10 = 10' Power Line Connector (included w/each driver)

NALTL-30 = 30' Power Line Connector

NATL-302W = Power Line Splitter, White

Example: **NAPKED-5060W** = 12V 60W Constant Voltage Dimmable Hardwire Electronic Driver