













# 4" LINE VOLTAGE SQUARE TRIM SERIES DOWNLIGHT, PINHOLE, ADJUSTABLE, LENSED

Project: \_\_\_\_\_

Fixture Type: \_\_\_\_\_

Location: \_\_\_\_\_

Contact/Phone: \_\_\_\_\_

Trim Series	Dimensions	Aperture	Catalog No.	Housing/Lamp Compatibility
 <b>Square Downlight</b>	 5"	 2-5/32"	<b>17SQ-HZ-WH</b> - Haze, White Trim <b>17SQ-W-WH</b> - White, White Trim <b>17SQ-B-WH</b> - Black, White Trim <b>17SQ-WHZ-WH</b> - Wheat Haze, White Trim	IC1/IC1W/IC1S: 50W PAR20 (Requires T599 socket extender), 39W PAR20, 30W R20 IC1P/TC1/TC1S/TC1R: 50W PAR20, 50W R20 ICPL/PL426 Series: 26W ICPL/PL418 Series: 18W ICPL/PL413 Series: 13W IC1LED/IC1RLED and IC1LWD/IC1RLWD Series
 <b>Square Pinhole</b>	 5"	1-1/4"	<b>13SQ-WH</b> - White Trim	IC1/IC1W/IC1S: 39W PAR20 (Requires T599 socket extender), 35W PAR20, 30W R20 IC1P: 50W PAR20, 30W R20 TC1/TC1S/TC1R: 50W PAR20, 50W R20 ICPL/PL426 Series: 26W ICPL/PL418 Series: 18W ICPL/PL413 Series: 13W IC1LED/IC1RLED and IC1LWD/IC1RLWD Series
 <b>Square Flush Gimbal</b>	 5" Adjustment: 35° Vertical		<b>440SQ-WH</b> - White Trim <b>440SQ-BL</b> - Black Trim	IC1/IC1W/IC1S: 35W MR16 120V GU10 Base IC1P/TC1/TC1S/TC1R: 50W MR16 120V GU10 Base  <b>All of the above requires Juno part# GU10-WHIP</b>
 <b>Square Frosted Lens with Clear Center</b>	 5"		<b>12SQ-W-WH</b> - Perimeter Frosted Lens, White Trim	IC1/IC1W/IC1S: 50W PAR20 (Requires T599 socket extender), 30W R20 IC1P/TC1/TC1S/TC1R: 50W PAR20, 50W R20 ICPL/PL426 Series: 26W ICPL/PL418 Series: 18W ICPL/PL413 Series: 13W IC1LED/IC1RLED and IC1LWD/IC1RLWD Series

