

## NEX-751-LED

### Steel Body NYC Approved Emergency Lights

Source: 4.8W Normal

2W or 3W Emergency Operation

Type \_\_\_\_\_

Project \_\_\_\_\_

Catalog No. \_\_\_\_\_

Notes \_\_\_\_\_

#### PRODUCT DESCRIPTION

Rugged 20 gauge steel luminaires comply with the latest New York City codes and performance standards. Available in exit or exit/emergency combination units

#### FEATURES

- 120/277VAC Dual voltage operation
- 20-gauge steel housing with white powder coating
- Large 8" font with 1" stroke
- Includes single and double faces
- Two or three glare free, adjustable round LED heads
- Removable knockout chevron directional arrows
- Illuminates for 90 minutes during power failure
- Meets City of New York state codes

#### ELECTRICAL

**Voltage:** 120V or 277V dual input

**Wattage:** 4.8W Normal, 2W or 3W Emergency Operation

**Light Source:** LED

**Circuitry Protection:** Solid State

**Construction:** Low profile, snap-together housing constructed of 20 gauge steel. Snap-out knockouts for wiring.

**Face:** Both double and a blank face are included with 8" red letters and 1" stroke. Knockout directional chevrons.

**Emergency:** Two or three 1W / 100lm per head LED emergency lights.

**Mounting:** Wall or side mount. All mounting hardware included.

**Battery:** Ni-Cad 3.6V 600mAh per head battery offers 90 minute emergency operation on fully charged battery.


**Testing:** High-charge / ready operation indicator light and test button.

#### LABELS AND LISTINGS

- UL Listed
- New York City Approved
- NFPA-101
- Suitable for damp location



#### PRODUCT IMAGES AND DIMENSIONS



## Steel Body NYC Approved Emergency Lights

Catalog No. \_\_\_\_\_

**NEX-751LED/R2** = NYC Approved Steel LED Exit with Two 12W Adjustable Heads, Battery Backup, Red

**NEX-751LED/R3** = NYC Approved Steel LED Exit with Three 9W Adjustable Heads, Battery Backup, Red

Example: **NEX-751-LED/R2** = NYC Approved Steel LED Exit with Three 12W Adjustable Heads, Battery Backup, Red