#### NM2-2RDC

2" M2 Round LED Recessed Downlight Source: 6W, 8W or 10W LED

400lm, 600lm or 850lm

#### PRODUCT DESCRIPTION

M2 downlight series features quality and convenience with easy installation for insulated or non-insulated applications. Luminaires can be configured into multiple options with trim accessories and produces over 850 lumens.

#### **FEATURES**

- · No housing required IC Air-Tight rated
- Easy installation for remodel or new construction applications
- Variety of trim accessories to configure desired appearance
- Quick disconnect allows for extended lengths
- 400lm, 600lm or 850lm LED packages
- 2700K, 3000K or 4000K @ 90+ CRI
- Triac or ELV dimming
- 5-year limited warranty
- **ENERGY STAR certified**
- cETLus Listed for Wet Locations

#### **SPECIFICATION**

Construction: Die-cast aluminum trims available in matte black or matte powder white finish. Open downlight includes a reflector with the same finish as trim; optional field changeable accessories are available; square trim, pinhole trim, wall wash trim, reflector inserts or baffle inserts.

Air Flow Restriction: Luminaire has factory installed gasket to restrict airflow from room into ceiling plenum to <2CFM (cubic feet per minute) in accordance with ASTM-283 Air-Tight requirements.

Clearance: IC rated luminaires are rated for direct contact with insulation (not spray foam insulation), no minimum clearance is required.

Junction Box: Prewired junction box includes quick connect to LED fixtures for ease of installation. Junction box includes two (400lm/600lm) or four (850lm) 1/2" trade size knockouts and snap on cover with 7" quick connect wire. Luminaire includes 5" (400lm/600lm) or 4" (850lm) quick connect wire.

Mounting: No housing is required, two tensions steel spring clips secure luminaire to ceiling. Accommodates ceiling thickness up to 3/4". New construction frame-in kits are available, see accessories.

ELECTRICAL	40	60	85
Input Voltage	120V		
Input Power	6W	8W	10W
Color Temperature	2700K or 3000K	2700K, 3000K, 4000K	2700K or 3000K
CRI	90+ CRI		
Dimming	Triac / ELV		
Operating Temp.	40°C max. 25°C max.		
Beam Spread	36° Flood		
Lifetime	60,000 hours @ L70		

Trims: M2 series is available in three lumen outputs with LED driver. Round trims can be converted to baffles, pinholes or wall wash in the field with optional trims and inserts.

#### **OPTIONAL TRIM ACCESSORIES**

NM2-2REFL: Reflector Insert for NM2-2RDC, Black or Haze NM2-2BAF: Baffle Insert for NM2-2RDC, Black or White NM2-2RPH: Round Pinhole Trim for NM2-2RDC, Black or White NM2-2RW: Round Wall Wash Trim for NM2-2RDC, Black or White NM2-2SDT: Square Trim for NM2-2RDC, Black or White

#### OPTIONAL MOUNTING ACCESSORIES

NM2-MLS1: One Head Multiple Lighting System Plate NM2-MLS2: Two Head Multiple Lighting System Plate NM2-MLS3: Three Head Multiple Lighting System Plate NF-R246: Universal New Construction Frame-In NFC-R275: New Construction Frame-In with Collar NM2-EW-4: 4' Quick Connect Linkable Extension Cable NM2-EW-10: 10' Quick Connect Linkable Extension Cable

#### LABELS AND LISTINGS

- cETLus Listed for Wet Locations
- **ENERGY STAR certified**
- 5-Year Limited Warranty
- FCC compliant
- Certified to the high efficacy requirements of California Title 24 JA8-2022














# Type Project Catalog No. Notes


### PRODUCT IMAGES AND DIMENSIONS



NM2-2RDCXXXXRR 400lm or 600lm Matte Black

NM2-2RDC85XXMPW 850lm Matte Powder White







Reflector Insert

NM2-2REFL



NM2-2BAF



NM2-2RPH NM2-2RW Round Wall Wash Trim Round Pinhole Trim





NM2-2SDT Square Trim

NM2-EW **Extension Cables** 

### 2" M2 Round LED Recessed Downlight

Trim Type	Lumens / Wattage	Color Temperature	Finish
NM2-2RDC = 2" Round Downlight	<b>40</b> = 400lm / 6W	<b>27</b> = 2700K	BB = Matte Black
	<b>60</b> = 600lm / 8W	<b>30</b> = 3000K	MPW = Matte Powder White
	<b>85</b> = 850lm / 10W		
	<b>60</b> = 600lm / 8W	<b>40</b> = 4000K	MPW = Matte Powder White

#### **M2 Trim Accessories**

Accessory Type	Finish
NM2-2REFL = Reflector for NM2-2RDC	<b>B</b> = Matte Black
	<b>HZ</b> = Haze
NM2-2BAF = Baffle for NM2-2RDC	B = Matte Black
NM2-2RPH = Round Pinhole Trim for NM2-2RDC	MPW = Matte Powder White
NM2-2RW = Round Wall Wash Trim for NM2-2RDC	
NM2-2SDT = Square Trim for NM2-2RDC	

### **Optional Mounting Accessories**

Accessory Type	Finish	
NM2-MLS1 = One Head MLS Plate	BB = Matte Black	
NM2-MLS2 = Two Head MLS Plate MPW = Matte Powder Wh		
NM2-MLS3 = Three Head MLS Plate		
NF-R246 = Universal New Construction Frame-In		
NFC-R275 = New Construction Frame-In with Collar		
NM2-EW-4 = 4' Quick Connect Extension Cable		
NM2-EW-10 = 10' Quick Connect Extension Cable		

Example: NM2-2RDC6030MPW = 2" M2 Round LED Recessed Downlight, 600lm / 8W, 3000K, Matte Powder White



### NM2-2RDC

### 2" M2 Round LED Recessed Downlight Accessories

Type
Project
Catalog No.
Notes



Reflector/Baffle Insert for NM2-2RDC

NM2-2REFLB Matte Black Reflector
NM2-2REFLHZ Haze Reflector
NM2-2BAFB Matte Black Baffle
NM2-2BAFMPW Matte Powder White Baffle
Replaces the reflector included with



Multiple Lighting System Plates

NM2-MLS1B 1 Head / Matte Black
NM2-MLS1MPW 1 Head / Matte Powder White
NM2-MLS2B 2 Head / Matte Black
NM2-MLS2MPW 2 Head / Matte Powder White
NM2-MLS3B 3 Head / Matte Black
NM2-MLS3MPW 3 Head / Matte Powder White
Converts multiple round LED luminaires into multiple
lighting system without a large housing.



Square Trim for NM2-2RDC


NM2-2SDTB Matte Black
NM2-2SDTMPW Matte Powder White
Converts the round trim included with
NM2-2RDC downlight into a square trim



Universal New Construction Frame-In

#### NF-R246

Universal new construction frame-in can be used to assist installing can-less recessed downlighting.





Round Pinhole Trim for NM2-2RDC

NM2-2RPHB Matte Black
NM2-2RPHMPW Matte Powder White
Converts the round trim included with
NM2-2RDC downlight into a round pinhole



Round Wall Wash Trim for NM2-2RDC


NM2-2RWB Matte Black
NM2-2RWMPW Matte Powder White
Converts the round trim included with
NM2-2RDC downlight into a round wall wash



New Construction Frame-In with Collar

#### NFC-R275

New construction frame-in can be used to assist installing can-less recessed downlighting.



# Luminaire Examples



## **PHOTOMETRICS**

### 2" M2 Round LED Recessed Downlight

Type

Project

Catalog No.


Notes

### **Test Information**

Test Number: NTR11363 Part Number: NM2-2RDC4027MPW Beam Spread: 36° Flood

Lumens: 445lm Wattage: 6.2W Efficacy: 72lpw

CCT / CRI: 2700K / 90 CRI Spacing Criteria (0°-180°): 0.6 Spacing Criteria (90°-270°): 0.6



### Illuminance at a Distance

Distance from Luminaire	FC at Nadir	Beam Diameter
2'	261fc	1'-4"
4'	65.3fc	2'-7"
6'	29fc	3'-11"
8'	16.3fc	5'-2"
10'	10.4fc	6'-6"

#### Zonal Lumen Summary

	-	
Zone	Lumens	% Luminaire
0-30	387	86.8
0-40	418	93.7
0-60	436	97.9
0-90	443	99.6
90-180	2	0.4
0-180	445	100

### Candela Table


Landela Table		
Vertical Angles	Candela	
0	1044	
5	993	
15	645	
25	264	
35	42	
45	14	

#### **Test Information**

Test Number: NTR11350 Part Number: NM2-2RDC4030MPW Beam Spread: 37° Flood Lumens: 464Im

Wattage: 6.23W Efficacy: 75lpw

CCT / CRI: 3000K / 90 CRI Spacing Criteria (0°-180°): 0.62 Spacing Criteria (90°-270°): 0.62



#### Illuminance at a Distance

Distance from Luminaire	FC at Nadir	Beam Diameter
2'	248fc	1'-4"
4'	61.9fc	2'-8"
6'	27.5fc	4'
8'	15.5fc	5'-5"
10'	9.9fc	6'-8"

#### Zonal Lumen Summary

	,	
Zone	Lumens	% Luminaire
0-30	393	84.7
0-40	434	93.5
0-60	455	98
0-90	464	99.9
90-180	1	0.1
0-180	464	100

#### Candela Table


Vertical Angles	Candela
0	990
5	950
15	639
25	272
35	51
45	15
45	15

### **Test Information**

Test Number: NTR11351 Part Number: NM2-2RDC6027MPW Beam Spread: 37° Flood

Lumens: 594lm Wattage: 7.8W Efficacy: 76lpw CCT / CRI: 2700k

CCT / CRI: 2700K / 90 CRI Spacing Criteria (0°-180°): 0.62 Spacing Criteria (90°-270°): 0.6



#### Illuminance at a Distance

Distance from Luminaire	FC at Nadir	Beam Diameter
2'	327fc	1'-4"
4'	81.9fc	2'-8"
6'	36.4fc	4'
8'	20.5fc	5'-5"
10'	13.1fc	6'-8"

#### Zonal Lumen Summary

Zone	Lumens	% Luminaire
0-30	505	85
0-40	557	93.7
0-60	582	97.9
0-90	593	99.8
90-180	1	0.2
0-180	594	100


#### Candela Table

Vertical Angles	Candela
0	1310
5	1251
15	847
25	359
35	85
45	19

### **Test Information**

Test Number: NTR11351 Part Number: NM2-2RDC6030MPW Beam Spread: 36° Flood Lumens: 641lm

Wattage: 8.1W Efficacy: 79lpw CCT / CRI: 3000K / 90 CRI Spacing Criteria (0°-180°): 0.6 Spacing Criteria (90°-270°): 0.6



#### Illuminance at a Distance

Distance from Luminaire	FC at Nadir	Beam Diameter	
2'	368fc	1'-4"	
4'	92.1fc	2'-7"	
6'	40.9fc	3'-11"	
8'	23fc	5'-2"	
10'	14.7fc	6'-6"	

#### Zonal Lumen Summary

Zone	Lumens	% Luminaire
0-30	547	85.4
0-40	597	93.2
0-60	626	97.8
0-90	639	99.8
90-180	1	0.2
0-180	641	100

#### Candela Table

Vertical Angles	Candela
0	1473
5	1403
15	909
25	372
35	67
45	21

# **PHOTOMETRICS**

2" M2 Round LED Recessed Downlight


Type
Project
Catalog No.
Notes

### **Test Information**

Test Number: NTR1431 Part Number: NM2-2RDC8530MPW Beam Spread: 38° Flood

Lumens: 882lm Wattage: 10.18W Efficacy: 87lpw

CCT / CRI: 3000K / 90 CRI Spacing Criteria (0°-180°): 0.62 Spacing Criteria (90°-270°): 0.62



### Illuminance at a Distance

manmanoo at a biotanoo			
FC at Nadir	Beam Diameter		
476fc	1'-5"		
119fc	2'-8"		
52.9fc	4'-1"		
29.7fc	5'-6"		
19fc	6'-11"		
	476fc 119fc 52.9fc 29.7fc		

#### Zonal Lumen Summary

Zone	Lumens	% Luminaire		Ve Ar
0-30	757	85.9		
0-40	824	93.4		
0-60	864	98		
0-90	880	99.8		
90-180	2	0.2		
0-180	882	100		

### Candela Table

Gariacia Tabic		
Vertical Angles	Candela	
0	1904	
5	1824	
15	1246	
25	540	
35	88	
45	27	